

Procedure to replace Flash

REQUIREMENTS:

- .- DMTools 3.18.4 (MB)
- .- Boot file, Flash file and LPFile :software approved in your country.
- .- Flash P/N: 53.G4901.001

PROCEDURE

- 1.- Replace Flash.
- 2.- Connect to DMTools 3.18.4(MB)

3 Press "Set E2P"								
B) Download	_							
File Option Yiew Download Calibration MmiTest IdCoding Service Tool Help								
🚽 🖳 🏵 🖳 🛒 🤋 🧏 🦙 🚱 D70 MH MR ZS	AS	RS						
Boot File C:\PROGRA~1\Service\SERVIC~1.4_M\r_flash_007.mot Flash File C:\Program Files\Service\V1.21\LT_EMEA\AS112140.apl LP File C:\Program Files\Service\V1.21\LANGPACK\ALP12143.MO Option Option								
✓ Download Code ✓ Set E2p Default ✓ DownLoad Language ✓ Set E2p Initial and PhoneBook								
Set EEProm Default Succeed!! Waiting for target ready7 s Waiting for target ready6 s Waiting for target ready4 s Waiting for target ready3 s Waiting for target ready2 s Waiting for target ready1 s Wait For Target Ready Send trigger E2p Command								
Download Progress								
Download Stop! Set E2P								



4.- Select "IdCoding", select "MS's IMEI" and press "Read". (All zeroes is read as default)

Bil Download File Option View I	Download Calibratio	n MmiTest IdCodir	q Service Tool	Help		_					
🚽 🖳 😣		ଃ № 😽	S D70	MH MR	ZS	AS	RS				
Boot File	C:\PROGRA~1	\Service\SERVIC	~1.4_M\r_flasi	h_007.mot							
Flash File C:\Program Files\Service\V1.21\LT_EMEA\AS112140.apl											
Production EEprom Edit Dialog											
Optio	Item Name:	MS's IMEI		T							
Set EE Waitin Waitin	IMEI Code : DOM :	Code: 0000000000000									
Waitin Waitin Waitin Waitin	Total Time: Failure Time:		Reset To Reset Failur	tal on Tim e ID	e						
Waitin Wait F Send t	Read	<u>W</u> rtie Writ	e Failure ID	<u>Q</u> uit							
Download Progress											
Downlo	a d	Stop!		Set E2P							



5 Write the new IMEI and press "Wrtie"												
			1					_				
Eile Option View Download Calibration MmiTest IdCoding Service Tool Help												
🤩 🔜 😣		% № ?		S D70	МН	MR	ZS	AS	RS			
Boot File C:\PROGRA~1\Service\SERVIC~1.4_M\r_flash_007.mot												
Flash File C:\Program Files\Service\V1.21\LT_EMEA\AS112140.apl												
Production EEprom Edit Dialog												
Coptio ✓ Dc ✓ Dc ✓ Dc ✓ Cc ✓ Set EE Waitin Waitin Waitin Waitin Waitin Waitin Waitin Waitin Waitin	Item Name: IMEI Code : DOM : Total Time: Failure Time:	MS's IM 3518630 	EI 00158996	5 Reset Tu eset Failu	otal on	Time						
Send 1	Send t Read Write Failure ID Quit											
	De	ownload f	Progress									
 Downlo	d	Stop) iI		©i Set i	2P						



6	Press a	gain ''	Set I	E2P'	,								
🚚 Do	wnload	Ŭ										_	
<u>F</u> ile g	Option <u>V</u> iew	Download	Calibrati	ion Mmi	iTest	IdCoding S	iervic	e Tool	Help				
5	🛄 🤅	3 🖳		?	N?		3	D70	МН	MR	ZS	AS	RS
	Boot File Flash File Option - Down Down Set EEPro Waiting for Waiting for Send trigg	C:\PR C:\Pr	OGRA~1 ogram F ogram F guage tt Succe eady eady eady eady ady ady omman	1\Servi iiles\Si iiles\Si iiles\Si 5 s 4 s 3 s 2 s 4 s 3 s 2 s 1 s d	ice\S ervic	SERVIC~1.4	_M\ r_EN ANGI 2p D 2p In	r_flasi MEA(A: PACK\ efault	h_007 S1121 ALP12 nd Ph	".mot 40.ap 2143.k	1000k		
			I	Downlo	oad I	Progress							
	 Down	load			X Stop))]			© Set E	2P			

7.- Then download last software's version