

Internal Name: (Padre)
Manufacturer: Compal Communications - Taiwan
Band: Dual 900/1800 or 850/1900
Memory Internal: ROM 64 MB, RAM 16 MB
User Memory: x MB for Programs
Memory External: No
Exp . SA Date: 2004/11/10



Customer Sync. SW: No

Service SW: Compal Service Tool, min. Version 1.05
Available at: <http://62.214.1.200>

Connectivity: via Headset Connector
Data Cable avail. at: <http://62.214.1.200> , Part No.: 2-00-1C-12000

Battery Eliminator: Part No.: 2-00-C3-10000
Available at: <http://62.214.1.200>

Antenna Gizmo: same as Shark , Part No.: 2-00-4E-10000
Available at: <http://62.214.1.200>

Flash/ Flex File Type: Seperate Main Code / Flex / Language Pack
Required Update SW: Compal Service Tool, , min. Version 1.05
Available at: <http://62.214.1.200>

Required Tools: Torx Size T5, Tweezers
Disassembly Tool MPX, C115....

Disassembly Tool available at: <http://62.214.1.200>, Part No. 0-00-00-40826

Req. Rep. Fixture: No

Solder Technologie: Lead

How to update SW?: Start up Service Tool, select Model Type , Power up Mobile and connect via serial cable, select Mobile Kit in the Service SW, browse for Main Code / Flex / Language Pack, press RS232 button, if finished - restart the Mobile.

Note: